

# **LED TROFFER**





























#### **Features & Benefits**

- 1. 130lm/w for options.
- 2. Die formed of 0.5mm cold-rolled steel body.
- 3. 0-10v dimming, universal voltage: 100-277v.
- 4. Wide application for: school, hospital, super market, office and warehouse.
- 5. Fully recessed luminaire fits standard T-Grid ceilings.
- 6. High-diffusion light-milky PC diffuser.
- 7. 5-year warranty.

#### **Product Dimension**



Model	L×W×H
HG-L249-22	603x603x45 (mm)/23.74"x23.74"x1.77"
HG-L249-24	1213x603x45 (mm)/47.76"x23.74"x1.77"
HG-L249-14	1213x303x45 (mm)/47.76"x11.93"x1.77"


## **Specification**

#### SN: WITH SENSOR


Part No.	Power	Input Voltage	Luminous Flux	Luminous Efficacy	CCT	Viewing Angle	Ra	PF	Warranty
HG-L249-14/36W-SN	36W		46801m						
HG-L249-14/50W-SN	50W		65001m						
HG-L249-22/24W-SN	24W	AC100-277V	31201m		3000K 3500K 4000K		>80	>0.9	5Years
HG-L249-24/24W-SN	24W		31201m						
HG-L249-24/36W-SN	36W		46801m	130lm/W					
HG-L249-24/42W-SN	42W		54601m	5000K		, 55			
HG-L249-24/50W-SN	50W		65001m						
HG-L249-22/20W/24W/36W	20W/24W/36W		52501m						
HG-L249-24/24W/36W/42W/50W	24W/36W/42W/50W		62501m						
HG-L249-24/24W/36W/42W/50W-SN	24W/36W/42W/50W		30001m						


The following multiple functions can be achieved according to customers' requests:

- 1. CCT options: 3000K,3500K, 4000K, 5000K.
- 2. Available with external or built-in microwave motion sensor.
- 3. Emergency: the power is 8W, it can still work in 1.5hrs while emergency situation.



# **Testing Report**






# **Applications**



Office



Library




**Bank** 




Supermarket

#### **OPTION**





#### **Installation manual**





# Lighting for the future





## **Important**

Read this instruction carefully before installation. Keep it for further reference. Make electrical and grounded connections in accordance with the national electrical code and any applicable code. Always turn off the power supply before installation. This product must be installed in accordance with the applicable installation code by a qualified electrician who is familiar with the construction and operation of the product and the hazards involved.

#### WARNING:

Risk of fire or electric shock. Fixture installation requires knowledge of luminaires electrical systems. If not qualified, DO NOT attempt installation. Contact a qualified electrician.

Risk of fire or electric shock. Suitable for wet locations. Always turn off the power supply before installation.

A Risk of fire or electric shock. Suitable for non-insulated surface and frame. DO NOT cover fixture with insulation liner or similar material.

DO NOT install fixture on unstable, loose or easily breakable surface.

⚠ DO NOT exert force on the surface of the fixture.

### Packing /weight

Model No.	Outer box (L*W*H)	Qty/Ctn (pcs)	N.W/pcs (lbs/Kg)	G.W/Ctn (lbs/Kg)
HG-L249-22	25.4"x4.13"x25.59" 645 x 105 x 650mm	2	7.04/3.2	16.3/7.4
HG-L249-14	13.58"x4.13"x49.21" 345 x 105 x 1250mm	2	8.36/3.8	19.14/8.7
HG-L249-24	25.4"x4.13"x49.21" 645 x 105 x 1250mm	2	13.2/6	31.9/14.5

#### Note

- 1. The installation and maintenance must be completed by electricians or professionals.
- 2.Please cut off the power before installation and maintenance.
- 3. The thermally insulating material is not allowed to cover the fixture.
- 4. Please keep away from the corrosive substance, and keep the fixture dry and clean.
- 5. Working temperature: -4°F~113°F, storage temperature: -22°F~140°F.